

*Official copies of these procedures are maintained at this website.
Before using a printed copy, verify that it is the most current
version by checking the document issue date on this website. Signed
copies of these official procedures are maintained at the Training Office*

C-A OPERATIONS PROCEDURES MANUAL

ATTACHMENT

4.56.b AGS Cursory Sweep Checklist

C-A-OPM Procedures in which this Attachment is used.		
4.56		

Hand Processed Changes

<u>HPC No.</u>	<u>Date</u>	<u>Page Nos.</u>	<u>Initials</u>
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____

Approved: _____ **Signature On File** _____
Collider-Accelerator Department Chairman Date

P. Ingrassia

AGS CURSORY SWEEP CHECKLIST

(Team Leader)_____ (Operator 2)_____

(Operator 3)_____ (Gate Watch)_____

Time:_____ Date:_____

Warning:

IF any personnel are encountered during the sweep, **THEN** determine whether their work will be completed in a short time. **IF** the work will take a long time, **THEN** contact the OC to see if the sweep should be aborted. **IF** the work will be completed in a short time, **THEN** write the name(s) of the workers at the end of the checklist and verify that they leave the enclosure **WITH** the sweep team **OR** that their names are recorded on the gate log sheet.

Prerequisites

- Three Operators to perform the sweep
- IF persons will remain in the ring during the sweep THEN a fourth person will act as gate watch.
- [C-A-OPM-ATT 4.56.b](#) "AGS CURSORY SWEEP CHECKLIST"(2 pages)
- [C-A-OPM-ATT 4.56.a](#) (last page)"AGS RING SWEEP" map (1 page) For Team Leader
- [C-A-OPM-ATT 4.1.a](#) "C-A GATE SECURITY LOG SHEET" (1 page) For gate watch (if used).
- C-A-OPM-ATT 4.1.a "C-A GATE SECURITY LOG SHEET" (1 page) For Operator 3.
- Key: BNL-13
- Two portable radios
- TLD, Alarming (chirping) Self Reading Dosimeter (SRD) and Pencil Type (SRD)
- Controlled or Restricted Access LOTO has been performed (C-A-OPM 2.6.1 Attachments a or b)
- AGS beam stops are closed (see MCR_2-1IJ7, MCR_2-1IJ8 -- F6/DH2-3)

Note:

IF the number of AGS Controlled Access entries exceeds 25 persons or the gate has been opened for more than four hours, **THEN** a cursory sweep is indicated. **IF** the AGS accelerated Heavy Ions before the entry, **THEN** perform the sweep as indicated. **IF** the AGS accelerated Protons before the entry, **THEN** consult the RSC Chairperson or the ESHQ Associate Chair to determine whether the sweep should include a person on the (inside) catwalk.

Note:

Use a gate watch if the sweep will take place while workers remain in the ring.

Check

- ____ 1. IF a gate watch is used, THEN instruct the gate watch to log, on the C-A Gate Security Log Sheet, all persons who exit the ring.
- ____ 2. IF a gate watch is used, THEN instruct the gate watch to **deny** entry the to the ring to those persons who do not have the approval of the Operations Coordinator.

CONTINUED ON REVERSE SIDE

- ___3. The sweep team enters the AGS ring at the South Gate. IF no gate watch is used, THEN lock the gate from the inside using the BNL-13 key.
- ___4. Team Leader instructs Operator 3 to stand static watch at the end of the South Gate ramp opposite E16-E17 main magnets.

Warning:

Operator 3 shall ensure that IF someone passes by, either on the catwalk or in the main aisle, THEN their name shall be recorded on C-A-OPM-ATT 4.1.a – C-A GATE SECURITY LOG SHEET

- ___5. IF one sweeper will walk the inside catwalk, THEN, both Operators proceed to the bridge over the main magnet at E15 and Operator 2 shall cross over the ring to the catwalk.
- ___6. Both Operators walk in the same direction (clockwise or counter-clockwise around the ring).
- ___7. When doors or reset stations are encountered during the sweep, one person shall check that all doors and/or reset station (as shown on the AGS RING SWEEP map) is closed and reset while the other sweeper stands static watch.

Note:

As one operator checks doors and resets, the other operator shall stand static watch.

- ___8. Team Leader shall record on the AGS RING SWEEP map:
- personnel encountered by the sweep team resets checked
 - unusual conditions
- ___9. After one circuit of the ring, both operators re-join Operator 3 at the South Gate Ramp.
- ___10. Three Operators sweep out of the enclosure.
- ___11. IF workers remain in the ring, THEN maintain a gate watch, ELSE, Team Leader shall reset the South Gate with the BNL13 key AND go to step 14 of this checklist.
- ___12. Check ONE of the following (item 12a or 12b).
- ___12a IF a gate watch was used, THEN Team Leader and Operator 3 shall enter the names of persons encountered in the ring (if any) onto the AGS Gate Security Log Sheet kept by the gate watch.
- ___12b IF a gate watch was not used AND persons were encountered in the ring, THEN Team Leader shall instruct Operator 3 to stand gate watch, AND shall verify that the names of persons encountered by Operator 3 (if any) and the names of persons encountered by the sweep team, are recorded on the C-A Gate Security Log Sheet kept by the gate watch.
- ___13. When all persons have exited the ring, reset the South Gate with the BNL13 key.
- ___14. When all persons have exited the ring, Team Leader shall verify that all AGS gates are secured by using the Security PC.